

# V-SERIES PANEL HARDWARE - INSTALLATION

## MICROPHONE CONNECTOR




Figure 2-87: Microphone Connector Pinout

The pin assignments for the microphone connector are:

Table 1: Microphone Socket Pinout


PIN	DESCRIPTION
1	Screen
2	Microphone input +
3	Microphone input -

Clear-Com offers different length gooseneck microphones

- ▶ 110/100 (100mm)
- ▶ 110/340 (340mm) - default
  - ▶ The 110/340 is also available as noise cancelling or hyper directional
- ▶ 110/490 (490mm)

## HEADSET CONNECTORS

The headset connector may be one of three types; XLR-4M (default), XLR-5F or XLR-7M.



PIN	DESCRIPTION
1	Microphone Screen
2	Microphone Input
3	Headphone Return
4	Headphone Output

More details are available in the V-series Instruction Manual

# V-SERIES PANEL HARDWARE - INSTALLATION

## HEADSET CONNECTORS

The headset connector may be one of three types; XLR-4M (default), XLR-5F or XLR-7.




Table 44: XLR5 Headset Pinout

Description	Pin Number
Microphone Screen	1
Microphone Input	2
Headphone Return	3
Left Headphone Output	4
Right Headphone Output	5




Figure 4-26: XLR-7M Headset Connector

Pin	Description
1	Microphone -ve
2	Microphone +ve
3	Ground
4	Left Headphone Output
5	Right Headphone Output
6	PTT1
7	PTT2/Headset Detect